

| Typ<br>MINIKOM | Rozměr<br>[mm]<br>(v/š/h) | Hmotnost<br>[kg] | Typ<br>MINIVARKOM | Rozměr<br>[mm]<br>(v/š/h) | Hmotnost<br>[kg] | Výkon<br>[kvar] | Přívodní<br>vedení<br>proud [A] |
|----------------|---------------------------|------------------|-------------------|---------------------------|------------------|-----------------|---------------------------------|
| EM-10/10       | 600/                      | 20               | EMV-10/10         | 600/                      | 23               | 10 (10x1)       | 20                              |
| EM-11/11       | 600/                      | 20               | EMV-11/11         | 400                       | 23               | 11 (11x1)       | 22                              |
| EM-13/13       | 254                       | 20               | EMV-13/13         | (600)/                    | 23               | 13 (13x1)       | 26                              |
| EM-15/15       |                           | 22               | EMV-15/15         | 250                       | 24               | 15 (15x1)       | 31                              |
| EM-18/9        |                           | 23               | EMV-18/9          | 600/                      | 28               | 18 (9x2)        | 37                              |
| EM-22/11       |                           | 24               | EMV-22/11         | 600/                      | 30               | 22 (11x2)       | 45                              |
| EM-29/9        |                           | 25               | EMV-29/9          | 250                       | 30               | 29 (9x3,15)     | 60                              |
| EM-34/11       | 900/                      | 29               | EMV-34/11         | 800/                      | 38               | 34 (11x3,15)    | 71                              |
| EM-41/13       | 600/                      | 32               | EMV-41/13         | 600/                      | 41               | 41 (13x3,15)    | 84                              |
| EM-47/15       | 254                       | 33               | EMV-47/15         | 250                       | 42               | 47 (15x3,15)    | 99                              |
| EM-53/17       |                           | 33               | EMV-53/17         |                           | 44               | 53 (17x3,15)    | 109                             |
| EM-59/19       |                           | 36               | EMV-59/19         |                           | 45               | 59 (19x3,15)    | 119                             |
| EM-68/11       |                           | 36               | EMV-68/11         |                           | 47               | 68 (11x6,25)    | 142                             |
| EM-75/12       |                           | 36               | EMV-75/12         |                           | 47               | 75 (12x6,25)    | 155                             |
| EM-75/15       |                           | 38               | EMV-75/15         |                           | 50               | 75 (15x5)       | 155                             |
| EM-81/13       |                           | 38               | EMV-81/13         |                           | 49               | 81 (13x6,25)    | 160                             |
| -              |                           |                  | EMV-93/15         | 800/                      | 62               | 93 (15x6,25)    | 191                             |
| -              |                           |                  | EMV-100/8         | 800/                      | 62               | 100 (8x12,5)    | 206                             |
| -              |                           |                  | EMV-112/9         | 250                       | 64               | 112 (9x12,5)    | 232                             |
| -              |                           |                  | EMV-125/5         |                           | 65               | 125 (5x25)      | 258                             |

**Rozváděče MINIKOM a MINIVARKOM**